EE331 Term 1, 2006

QUIZ # 1

Name: Cameron Buskell Student ID: 10196422

- *45 Minutes. No materials are allowed (Number) indicates weighting.*
- *No interaction with another student is allowed during the exam. Cheating will not be tolerated.*

1. Numbers are stored in the order in which they are printed out in _____ Endian. (0.4)
2. There are two ways to represent real numbers in computer. Which one is faster and more accurate? (0.4) Binary
3. From flip-flops and latches, which one are level sensitive? (0.4) _____
4. What are the functions of the accumulator register in a computer arithmetic/logic unit? (1)

5. How many pins are required for a 16K ×8 RAM with common I/O and one CS input? Consider other pins as well if necessary. (1)

6. The MCM6209C is a 64K × 4 static RAM chip. How many of these are needed to form a 256K × 16 module? (1)

7. Determine how many bits each of the following registers can hold? (0.7)

   PC, DAR, IR, DR, ACCA, Address Latch/Buffer, Data Buffer

8. Assume that initially [PC] = C807, [A] = 09, and [C457] = 08. (0.6)

```
C807   BB      ; ADDA
C808   C4
C809   57
```

   At the completion of this instruction, [PC] = _____, [A] = _____, and [C457] = _____.

9. Examine the following 68HC11 MPU program and answer the following questions: (2)

```
E230   B6      ;LDAA
E231   F6
E232   07
E233   B0      ;SUBA
E234   F6
E235   07
E23D   3E      ;WAI
```

   (a) How many times does the address F607 appear on the address bus? _____

   (b) How many times does the MPU perform a memory READ operation except WAI instruction? A WRITE operation?

   _____

   (c) How many times is a new word loaded into the IR? _____

   (d) How many times is a new word loaded into the DR? _____

   (e) How many times is a new word loaded into ACCA? _____

   (f) What are the final contents of ACCA? _____

   (g) Repeat problem (b) including WAI. _____

10. Assume that the following operands are initially stored in data memory: [C350] = 0A, [C351] = 01, [C352] = FF. (2)

```
C300   B6      ;LDAA
C301   C3
C302   50
C303   B0      ;SUBA
C304   C3
C305   51
C306   27      ;BEQ
C307   03
C308   B7      ;STAA
C309   C3
C30A   52
C30B   3E      ;WAI
C30C   ??
```

7. Determine how many bits each of the following registers can hold? (0.7)

PC, DAR, IR, DR, ACCA, Address Latch/Buffer, Data Buffer

8. Assume that initially [PC] = C807, [A] = 09, and [C457] = 08. (0.6)

```
C807    BB      ; ADDA
C808    C4
C809    57
```

At the completion of this instruction, [PC] = _____, [A] = _____, and [C457] = _____.

9. Examine the following 68HC11 MPU program and answer the following questions: (2)

```
E230    B6      :LDAA
E231    F6
E232    07
E233    B0      :SUBA
E234    F6
E235    07
E23D    3E      :WAI
```

(a) How many times does the address F607 appear on the address bus? _____

(b) How many times does the MPU perform a memory READ operation except WAI instruction? A WRITE operation?

_____

(c) How many times is a new word loaded into the IR? _____

(d) How many times is a new word loaded into the DR? _____

(e) How many times is a new word loaded into ACCA? _____

(f) What are the final contents of ACCA? _____

(g) Repeat problem (b) including WAI. _____

10. Assume that the following operands are initially stored in data memory: [C350] = 0A, [C351] = 01, [C352] = FF. (2)

```
C300    B6      ;LDAA
C301    C3
C302    50
C303    B0      ;SUBA
C304    C3
C305    51
C306    27      ;BEQ
C307    03
C308    B7      ;STAA
C309    C3
C30A    52
C30B    3E      ;WAI
C30C    ??
```

(a) What will be [A] and [C352] at the completion of the program? _____

(b) Assume that [C351] = 0A initially and repeat (a). _____

11. A certain program has the op code for a BEQ instruction at address 07A2. What offset should be used to cause branching to 07BC? (0.5)

3.6 /10